



### Power Field Effect Transistor

### **GENERAL DESCRIPTION**


This high voltage MOSFET uses an advanced termination scheme to provide enhanced voltage-blocking capability without degrading performance over time. In addition, this advanced MOSFET is designed to withstand high energy in avalanche and commutation modes. The new energy efficient design also offers a drain-to-source diode with a fast recovery time. Designed for high voltage, high speed switching applications in power supplies, converters and PWM motor controls, these devices are particularly well suited for bridge circuits where diode speed and commutating safe operating areas are critical and offer additional and safety margin against unexpected voltage transients.

#### **FEATURES**


- Reduced Gate Charge
- ◆ Ultra Low On-Resistance Provides Higher Efficiency
- Avalanche Energy Specified
- Source-to-Drain Diode Recovery Time Comparable to a Discrete Fast Recovery Diode
- Diode is Characterized for Use in Bridge Circuits
- ♦ I<sub>DSS</sub> and V<sub>DS</sub>(on) Specified at Elevated Temperature

### PIN CONFIGURATION

### SYMBOL



TO-220/TO-220FP



### **ABSOLUTE MAXIMUM RATINGS**

Rating		Value	Unit
Drain to Current — Continuous		7.5	Α
- Pulsed	$I_{DM}$	22.5	
Gate-to-Source Voltage — Continue	$V_{GS}$	±30	V
Total Power Dissipation – TO220		165	W
– TO220FP		32	
Derate above 25℃ - TO220		1.34	W/°C
– TO220FP		0.38	
Operating and Storage Temperature Range	$T_J$ , $T_{STG}$	-55 to 150	$^{\circ}\!\mathbb{C}$
Single Pulse Drain-to-Source Avalanche Energy $-T_J = 25^{\circ}$ C ( $V_{DD} = 100V$ , $V_{GS} = 10V$ , $I_L = 7A$ , $L = 10mH$ , $R_G = 25\Omega$ )		245	mJ
Thermal Resistance — Junction to Case -TO220	$\theta_{JC}$	0.77	°C/W
<ul> <li>Junction to Case -TO220FP</li> </ul>		3.4	
<ul> <li>Junction to Ambient -TO220, TO220FP</li> </ul>	$\theta_{JA}$	62.5	
Maximum Lead Temperature for Soldering Purposes, 1/8" from case for 10 seconds		260	$^{\circ}\!\mathbb{C}$





# Power Field Effect Transistor

### **ORDERING INFORMATION**

Part Number	Package
GPT08N65GN220	TO-220
GPT08N65DGN220FP	TO-220 Full Package

<sup>\*</sup>Note: G: Suffix for Pb Free Product

### **ELECTRICAL CHARACTERISTICS**

Unless otherwise specified,  $T_J = 25^{\circ}C$ .

			GPT08N65			
Characteristic		Symbol	Min	Тур	Max	Units
Drain-Source Breakdown Voltage		$V_{(BR)DSS}$	650			V
$(V_{GS} = 0 \text{ V}, I_D = 250 \ \mu \text{ A})$						
Drain-Source Leakage Current		I <sub>DSS</sub>			1	uA
$(V_{DS} = 650 \text{ V}, V_{GS} = 0 \text{ V})$						
Gate-Source Leakage Current-Forward		$I_{GSSF}$			100	nA
$(V_{gsf} = 30 \text{ V}, V_{DS} = 0 \text{ V})$						
Gate-Source Leakage Current-Reverse		$I_{GSSR}$			100	nA
$(V_{gsr} = 30 \text{ V}, V_{DS} = 0 \text{ V})$	V, V <sub>DS</sub> = 0 V)					
Gate Threshold Voltage		$V_{GS(th)}$	2.5		4.5	V
$(V_{DS} = V_{GS}, I_{D} = 250 \ \mu A)$						
Static Drain-Source On-Resistance (V <sub>GS</sub> = 10 V, I <sub>D</sub> = 4A) *		R <sub>DS(on)</sub>			1.2	Ω
Forward Transconductance (V <sub>DS</sub> = 15 V, I <sub>D</sub> = 4A) *		<b>g</b> fs		7		S
Input Capacitance	$(V_{DS} = 25 \text{ V}, V_{GS} = 0 \text{ V},$	$C_{iss}$		1290		pF
Output Capacitance	( 20	Coss		118.8		pF
Reverse Transfer Capacitance	f = 1.0 MHz)	$C_{rss}$		10.49		pF
Turn-On Delay Time	0/ 005 1/ 1 0 4	$t_{d(on)}$		24.5		ns
Rise Time	$(V_{DD} = 325 \text{ V}, I_D = 8 \text{ A},$ $V_{GS} = 10 \text{ V},$ $R_G = 9.1\Omega) *$	t <sub>r</sub>		28.3		ns
Turn-Off Delay Time		$t_{d(off)}$		45.2		ns
Fall Time		t <sub>f</sub>		25.7		ns
Total Gate Charge	(V <sub>DS</sub> = 520 V, I <sub>D</sub> = 8 A,	$Q_g$		30		nC
Gate-Source Charge		$Q_{gs}$		6.35		nC
Gate-Drain Charge	$V_{GS} = 10 \text{ V})^*$	$Q_{gd}$		11.8		nC
SOURCE-DRAIN DIODE CHARACTE	RISTICS					
Forward On-Voltage(1)	(I <sub>S</sub> = 8A, V <sub>GS</sub> = 0 V,	V <sub>SD</sub>			1.5	V
Forward Turn-On Time		t <sub>on</sub>		**		ns
Reverse Recovery Time	$d_{IS}/d_t = 100A/\mu s)$	t <sub>rr</sub>		390		ns

<sup>\*</sup> Pulse Test: Pulse Width  $\leq$ 300 $\mu$ s, Duty Cycle  $\leq$ 2%

<sup>\*\*</sup> Negligible, Dominated by circuit inductance



## POWER FIELD EFFECT TRANSISTOR

### TYPICAL ELECTRICAL CHARACTERISTICS




Fig 1. On-Resistance Vs. Temperature




Fig 3. Typical Output Characteristics




Fig.2 Breakdown Voltage Variation vs. Temperature




Fig 4. Typical Transfer Characteristics





## Power Field Effect Transistor




Fig 5. Typical Capacitance Vs. Drain-to-Source Voltage





Fig 6. Typical Gate Charge Vs. Gate-to-Source Voltage






# Power Field Effect Transistor

### **PACKAGE DIMENSION**



C1: -1	Dimensions	In Millimeters
Symbol	Min.	Max
Α	4.40	4.80
A1	2.10	2.84
Ъ	0.71	0.91
b1	1.17	1.37
С	0.30	0.60
c1	1.17	1.47
D	9.40	10.60
Е	8.40	9.60
е	2.54 TYP.	
e1	4.90	5.60
F	3.00 REF.	
Φ	3.50 REF.	
h	0.00	0.30
L	12.50	14.00
L1	3.50	4.00

#### TO-220F



Cross b = 1	Dimensions In Millime		
Symbol	Min.	Max	
Α	3.80	4.70	
A1	1.3 REF.		
A2	2.20	3.20	
A3	2.10	3.20	
Ъ	0.30	0.95	
b1	1.00	1.75	
b2	1.00	1.75	
b3	0.50	0.80	
С	0.30	0.90	
D	9.90	10.40	
Е	14.60	16.20	
е	2.54 TYP.		
F	3.00 REF.		
Φ	3.50 REF.		
h	0.00	0.30	
L	28.00	30.00	
L1	3.20	3.55	





### Power Field Effect Transistor

#### **IMPORTANT NOTICE**

Great Power Microelectronic Corporation (GP) reserves the right to make changes to its products or to discontinue any integrated circuit product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

A few applications using integrated circuit products may involve potential risks of death, personal injury, or severe property or environmental damage. GP integrated circuit products are not designed, intended, authorized, or warranted to be suitable for use in life-support applications, devices or systems or other critical applications. Use of GP products in such applications is understood to be fully at the risk of the customer. In order to minimize risks associated with the customer's applications, the customer should provide adequate design and operating safeguards.



虹冠電子工業股份有限公司 Champion Microelectronic Corporation Web:http://www.champion-micro.com/



深圳市冠顺微电子股份有限公司 Shenzhen Great Power Co., Ltd Web:http://www.grtpower.com

臺灣	深圳
新北市汐止區新台五路一段 96 號 21F	深圳市福田区深南大道 7002 号财富广场 A 座 4V,
21F., No. 96, Sec. 1, Sintai 5th Rd., Sijhih City, Taipei County 22102, Taiwan, R.O.C.	4V, Tower A, Fortune Plaza, No. 7002, Shennan Road, Futian District, Shenzhen City, China PC: 518040
TEL: +886-2-2696 3558	TEL: +86-755-83709176
FAX: +886-2-2696 3559	FAX: +86-755-83709276